

VISTA-10SE

With six zones and 5800 wireless zone expansion, the VISTA-10SE is the industry's most economical and sophisticated panel with light and appliance control.

Dependable features to meet your most demanding installations:

- Six hardwired zones standard
- Expands to 22 total zones when using 5800 wireless
- Seven user codes
- Two-method downloading
- Supports up to four relays
- False alarm prevention features
- Fast and easy E2 programming mode



**Control
Panel**

FEATURES:

End users will appreciate the easy-to-use convenience and control features of the VISTA-10SE:

- Wireless Remote Control: 5804 Four-Button Wireless Key, 5804BDV Bi-Directional Wireless Key with system status feedback or 5804WATCH Four Button Wireless Key
- Single or Dual Button Wireless Personal Panic: 5802MN and 5802MN2
- Home Automation: Activates lights, appliances, garage doors, and numerous other devices
- VISTA Interactive Phone Module (VIP): Gives the end user control of their system from any touchtone phone; the 4286 VIP Module responds in clear English, with over a 100 word vocabulary
- Full English Display Keypads: Provides clear understanding of system status and zone locations
- Paging: Openings, closings, alarm and trouble messages can be sent directly to a pager, allowing system status to be confirmed; parents can use this feature to verify that their children have arrived home
- QUICK EXIT: Enables users to leave the house for a brief time without disarming the system

**ADEMCO
GROUP**

VISTA-10SE

SPECIFICATIONS:

Electrical

- 500 mA, Aux - 12 VDC
- 16.5 VAC/25 VA transformer
- Alarm output 12 VDC, 2.0 amps max
- For UL installations, combined Aux and alarm output cannot exceed 600mA

Output Control

- Supports one relay board (part number 4204) for four relays

Zones

- Six hardwired zones
 - Selectable response: 10msec, 350msec, 750msec
 - Expandable to 22 zones using 5800 wireless
 - 16 zone types to choose from
 - Programmable swinger suppression

Supported Devices

Hardwired Expansion Devices

- 4204 supports up to four relays-15mA standby (each active relay draws an additional 40mA)
- Keypads
 - 6160/6139 Custom English (required for programming) - 150mA/40mA, 100mA/40mA
 - 6150/6128 fixed English LCD - 70mA/40mA, 40mA/20mA
- 4286 VIP Voice Module - 220mA
- Four-wire smoke detectors

Wireless Receiver Systems

- 5800 receivers
 - 5881ENL up to eight zones - 60mA
 - 5881ENM up to 16 zones - 60mA
- All receivers support
 - Diversity reception with two antennae
 - Remote mounting for best location
 - Unique supervision and low battery indications by point

Transmitters

- 5800 Series
 - Three-Volt Duracell lithium batteries
 - One mile range
 - Tamper is standard

Agency Listings

- UL Residential Fire and Burglary and CFM

Communications

- Touchtone or pulse
- Formats supported
 - ADEMCO Contact ID
 - ADEMCO 4 + 2 Express
 - ADEMCO Low Speed
 - Sescoa/Radionics
- 3 + 1, 4 + 1 and 4 + 2 reporting
- Reporting capabilities: Split, Dual, Split/Dual, Pager

**Control
Panel**

ORDERING:

Part No.	Description
VISTA-10SE	Control Panel