

VISTA-20SE

Control Panel



ADEMCO's cost effective, versatile VISTA-20SE is an eight-zone control panel that provides the ultimate in installation flexibility along with the features that your customers want.

FEATURES

- Eight hardwire zones standard
- Expands to 38 total zones (30 zones using 5800 wireless and/or 16 hardwired zones)
- 48 event log
- Two partitions with common area logic
- Built-in phone line cut monitor
- 15 user codes per partition
- Supports four relays or eight X-10 devices
- Fast and easy E2 Programming Mode
- Wireless remote control - single button system control with a wireless device
 - 5804 four button programmable wireless key
 - 5804BD bi-directional floor button programmable wireless key with system status feedback
- Home automation activates lights, appliances, garage doors and numerous other devices
- VIP phone module gives the end user ability to control the system from any touchtone phone
- Quick exit enables users to leave the house for a brief time without disarming the system
- Full English display keypads provide a clear understanding of system status and zone locations
- Chime by zone can be activated when the system is disarmed (this feature programs entrance and exit points to chime when opened)
- Paging sends openings, closings, alarm and trouble messages directly to a pager, allowing system status to be confirmed
- Ten custom alpha words
- False alarm reduction features

VISTA-20SE

Control Panel

SPECIFICATIONS

Electrical

- Aux power 12VDC, 600mA max
- Supports up to four AH batteries
- Seven hour standby at 400 mA aux load with 4 amp hour battery
- 16.5 VAC/25VA transformer
- Alarm output 12VDC, 2.0 amps max
- For UL installations, combined aux and alarm output cannot exceed 700mA

Output Control

- Supports one relay board (part number 4204) for four relays
- Optional X-10 transformer/interface (part number 4300) may be used to control up to eight X-10 receiving devices

Zones

- Eight hardwired zones
- Selectable response 10msec, 350msec, 750msec
- Assignable to either partition
- 16 zone types to choose from
- Programmable swinger suppression

Expansion Devices

Hardwired Expansion Devices

- 4219 - eight hardwired zones - 16mA
- 4204 - up to four relays - 15mA standby (each active relay draws an additional 40mA)
- 4229 - eight hardwired zones and two relays - 36mA
- Powerline Support - 4300 transformer/ interface

Accessories

- 4286 VIP Voice Module – 220mA
- 5881ENL RF Receiver supports up to eight zones – 60mA, 5881ENM supports up to 16 zones – 50mA, 5881ENH up to 40 zones – 50mA
- 5883 Transceiver supports up to 40 zones – 80mA
- Supports Eagle 1225 and 1221 boards

Keypads

- 6160 Custom English (required for programming) – 150mA/40mA (6160) 130mA/40mA (6139)
- 6160V Custom English with voice – 150mA/40mA
- 6148 Fixed English LCD – 70mA/30mA

- 6150 Fixed English LCD – 70mA/40mA (6150), 40mA/20mA (6128)
- 6150RF Fixed English LCD with built-in receiver 105mA/80mA
- 6150V Fixed English LCD with voice 70mA/40mA

Agency Listings

- UL Residential Fire and Burglary and CFM

Communications

- Touchtone or pulse
- Formats supported
 - ADEMCO contact ID
 - ADEMCO 4 + 2 Express
 - ADEMCO low speed
 - Sescoa/Radionics
- 3 + 1, 4 + 1 and 4 + 2 reporting
- Reporting capabilities
 - Split
 - Dual
 - Split Dual True dial tone detection
- Low battery reports 11.2 - 11.6 VDC
- AC loss and restoral reporting supported

ORDERING

VISTA-20SE Control Panel

Honeywell Security Group

ADEMCO
165 Eileen Way, Syosset, NY 11791
www.ademco.com

ADEMCO
A Honeywell Company